

The image shows a black CTEK RB 3000 portable booster connected to a car battery. The booster has a digital display showing '85%' and a power button. The car's engine compartment is visible in the background.

RB 3000

INSTANT STARTING POWER

The RB 3000 booster gives you instant power to start vehicles with dead 12V batteries. Packed with safety features, additional USB charging ports and a built-in flashlight, it's as versatile as it is reliable. Powerful, compact and ready to go, it ensures nothing gets in the way of life's journeys.

JUMP START DEAD 12V BATTERIES

Meet the RB 3000 portable booster. Compact in size, yet packed with 3000A battery peak current, it is built to jump start most 12V batteries with ease. It has advanced safety features, including spark-proof technology and reverse polarity protection, so you can use it confidently to get back on the move. But it's more than just a jump starter. It's also a versatile power bank with USB charging ports for all your devices, and has a built-in LED flashlight with three lighting modes. You'll never miss a moment, no matter where your adventures take you - with the peace of mind that comes from Sweden's charging pioneers, CTEK.

PACKED WITH POWER, ALWAYS READY

The RB 3000 delivers instant starting power - reliably getting you back on the move. Whether it's helping you overcome an unexpected dead battery or providing power for devices on the go, it's always ready when you need it. Compact, smart and durable, it's the must-have essential to meet the challenges of every journey.

- Instant starting power - for up to 30 starts on a single charge.
- Jump starts all kinds of 12V lead-acid batteries, including AGM, EFB, WET, GEL and Ca/Ca.
- Spark-proof technology and reverse polarity protection for safe use.
- Compact design for easy portability and storage.
- High-capacity USB powerbank plus a built-in flashlight with 3 lighting modes.
- Robust Swedish-inspired design for dependable performance.
- Charges phones, tablets and other electronics through built-in USB-A and USB-C ports.
- Comes with clamps, storage bag and user guide.
- Ergonomic design with intuitive LED indicators.
- 2-year warranty.



www.gobatteries.co.uk

Tel: +44 (0) 1926 400080 | email: sales@gobatteries.co.uk

CTEK

RB 3000



TECHNICAL DATA

BATTERY PEAK CURRENT	3000A / 30 starts
MAXIMUM CRANKING CURRENT	1980A
START CURRENT	Up to 1300A
INTERNAL BATTERY CAPACITY	16000mAh (4000mAhx4 / 59.2Wh)
FAST CHARGING TIME	2.5 hours
INTERNAL BATTERY PACK TYPE	4S1P
INTERNAL BATTERY CELL CHEMISTRY	Polymer Lithium-Ion
INPUT	USB-C PD 30W
OUTPUT	12V, USB-A QC3.0, USB-C PD30W
BATTERY TYPES	12 V: WET, MF, Ca/Ca, AGM, EFB, GEL
BATTERY CHEMISTRY	Lead acid
START VOLTAGE	2.5 V
AMBIENT OPERATING TEMPERATURE	-20 °C to +55 °C for output
AMBIENT STORAGE TEMPERATURE	0 °C to +55 °C
USER INTERFACE	Display
DIMENSIONS (L X W X H)	239 x 107 x 40 mm
NET WEIGHT (UNIT WITH CABLES)	1028 +/-10 g
DEGREE OF PROTECTION	IP65
DETACHABLE STARTING CABLE LENGTH OUTPUT	0.25 m
COOLING	Natural convection
MAINS ADAPTER CABLE LENGTH	1 m
MAINS ADAPTER CABLE TYPE	USB-C
WARRANTY	2 years

GUARANTEED QUALITY WITH CTEK

CTEK customer support is available to answer any questions related to charging and CTEK chargers. Safety, simplicity and flexibility characterizes all products and solutions developed and sold by CTEK. CTEK supply chargers to more than 70 countries throughout the world. CTEK is also a reliable OEM supplier to many of the world's most prestigious car and motorcycle manufacturers.

For more information visit WWW.CTEK.COM

www.gobatteries.co.uk

Tel: +44 (0) 1926 400080 | email: sales@gobatteries.co.uk

All products and product specifications are subject to change without notice, to improve reliability, function or design. In the event of product error, we reserve the right to inspect the product and verify the fault. All product returns are subject to our standard warranty terms.



CTEK